

AJD 200

John Deere
Mecc Alte
P 602



- ISO8528** MSO 8529
- SZUTEST**
- CE**

2000/14/EC MSO 8529

0.8 PF

U _N	U ₁	U ₂	U ₃	U ₄	Amp
400/230	200,00	160,00	180,00	144,00	260,00

ISO 8528 (ESP) ... ISO 8528 ... ISO 3046

Standard Specifications

Technical specifications and standards for the generator, including ISO 8528 and ISO 3046 compliance.

Generator Performance

ALTERNATOR
 - Voltage regulation
 - Efficiency
 - Power factor
 - Frequency stability

TRANSFER SWITCH
 - Switching capacity
 - Breaker type
 - Control system

AJD 200

John Deere
Mecc Alte
P 602

AKS 17012014

Manufacturer	John Deere			
Model	6068 H			
Power (kW)	1500	183,00	245,00	[245,00HP]
Power (kVA)	1500			
Length (mm)	L	6,800		
Width (mm)	106 X127			
Height (mm)	17:1			
Speed (rpm)	1500			
Weight (kg)	L	32,00		
Weight (kg)	L	36,50		
Absorbed Air Discharge ReSourceKey.Text	11,50			
Price (€)	262,10			
Price (€)	32,00			
Temperature (°C)	603,00			
Voltage (V d.c.)	12 V d.c.			
Load	41,00	31,30	20,50	

AKS 17012014

Manufacturer	Mecc Alte			
Model	ECO 38-1SN			
Frequency (Hz)	50			
Voltage (V)	180,00			
Cos φ	0,80			
Speed (rpm)	3			
Weight (kg)	400/230			
Weight (kg)	259,00			

AKS 17012014

Model	Price (€)	Price (€)	Price (€)	Price (€)	Price (€)
AJD 200	1570,00	2392,00	1150,00	1521,00	380,00
AK 50	1990	3402	1160	1866	380

AJD 200

John Deere
Mecc Alte
P 602

⌂ √ ^ | | ∫ ≤ ∫ ≥ | L | ∫ | : √ ~ ∴ : ∫ ≥ | ∞ ∴ ~ √

1 P 602 - → √ ∴ ~ | ∫ ∫ √ ∞ ∴ : √ ∞ ∫ | ∫ √ >>



- 1 Main status display.
- 2 Display scroll button.
- 3 Page(information) button.
- 4 Common alarm indicator.
- 5 Status LED's.
- 6 Operation selecting buttons.

2 ↔ : √ ∞ ∴ : ∫ ≥

DSE, model 6020 Auto Mains Failure control module.
Battery charger input 198-264 volt , output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
Emergency stop push button and fuses for control circuits.

3 ↔ : ∫ ∴ ~ ∴ ∞ U ∫ √ >> √ ∴ ∴ U : √ ∴ U √

Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

4 ↔ : ∫ ~ √ ||

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen. Set. from Alternator)

5 ↑ ∫ ∴ U ∞ ∴ : √ ∞ ∫ | ∫ √ >> L | ∫ | : √ ~ ∴ : ∴ ∫ ∫

The DSE 6020 is a standard control module for our generator sets up to 200kVA and it has been designed to start and stop diesel and gas generator sets. The DSE 6020 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts. Module monitors the mains supply and switch over to the generator when the mains power fails. The DSE6020 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

→ ~ √ ∫ √ : ~ ∫ ≥ | ∴ ∴ | ∫ √ √ U √ ∫ √ √

- Microprocessor controlled.
- LCD display makes information easy to read.
- 4-line, 64 x 132 pixel display.
- Automatically transfers between mains (utility) and generator power.
- Manual programming on front panel.
- User-friendly set-up and button layout.
- Remote start.
- Event logging (5) showing date and time.
- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

AJD 200

John Deere
Mecc Alte
P 602

↓ ↑ ^ ∫ | : v ~ | ∫ ≤ ∫ ≥ | :: : v α :: : ≥

- ENGINE
 - Engine speed.
 - Oil pressure.
 - Coolant temperature.
 - Run time.
 - Battery volts.
 - Configurable timing.
- GENERATOR
 - Voltage (L-L, L-N).
 - Current (L1-L2-L3).
 - Frequency.
- MAINS
 - Voltage (L-L, L-N).
 - Frequency.
 - Mains ready.
 - Mains enabled.
 - Gen. Set ready.
 - Gen. Set enabled.

→ ≈ | ∫ √ ^ √ ≡ v ~ ≥

- WARNING
 - Charge failure.
 - Battery Low/High voltage.
 - Fail to stop.
 - Low /High generator voltage.
 - Under/over generator frequency.
 - Over /Under speed.
 - Low oil pressure.
 - High coolant temperature.
- SHUT DOWNS
 - Fail to start.
 - Emergency stop.
 - Low oil pressure.
 - High coolant temperature.
 - Over /Under speed.
 - Under/over generator frequency.
 - Under/over generator voltage.
 - Oil pressure sensor open.
 - Coolant temperature sensor open.
- ELECTRICAL TRIP
 - Generator over current.

⇨ :: ∞ v :: ∫ ∫ ≥ | :: :: : α | ∫ ∫ :: :: ~ v

Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

→ ~ √ ∫ √ : ~ ≥

Electrical Safety / EMC compatibility BS EN 60950
Electrical business equipment.
BS EN 61000-6-2 EMC immunity standard.
BS EN 61000-6-4 EMC emission standard

⇨ : v α :: : ∫ ∫ > ^ √ : > ∫ U v √ U U ∞ ∫ ∞ ∫ > ~ :: : √

Battery charger is manufactured with switching-mode and SMD technology and has high efficiency. Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC. Proline 2405 has fully output shot circuit protection and can be used as a current source. Proline 1205/2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives. The charger is fitted with a protection diode across the output. Connect charge fail relay coil between positive output and CF output. They are equipped with RFI filter to reduce electrical noise radiated from the device. Galvanically isolated input and output typically 4kV for high reliability.

